

Internet trading hardware configuration.

- 1) Internet Explorer 5.0 & Above
- 2) RAM = 512 MB ram (Normal User)
- 3) RAM = 1 GB ram (Dealer users)
- 4) Hard disk Space minimum 20 GB
- 5) Operating System = Windows XP & Above
- 6) Bandwidth = 128 kbps & above

Tr@ade X'pro technical requirement & its global IP address

Tr@de X'pro Internet Users connecting through Domain, request is round robin between the servers. (200.87.57.98, 202.87.57.99, 202.87.57.103, 202.87.57.104)

Sr. No.	Global IP	Required Ports	Broadcast Ports	Domain
1	202.87.57.98	64700, 65000, 56000	35175 , 35218, 35219, 35701, 35193, 35194, 56001	www.anandrathi.co.in
2	208.87.57.99	64700, 65000, 56000	35175 , 35218, 35219, 35701, 35193, 35194, 56001	www.anandrathi.org
3	202.87.57.103	64700, 65000, 56000	35175 , 35218, 35219, 35701, 35193, 35194, 56001	www.anandrathi.co.in
4	202.87.57.104	64700, 65000, 56000	35175 , 35218, 35219, 35701, 35193, 35194, 56001	www.anandrathi.org

Check following commands

Go to Start – Run – type CMD & press Enter key on keyboard
Command Prompt will open

```
telnet 202.87.57.98 65000
```

```
telnet 202.87.57.98 64700
telnet 202.87.57.98 56000
```

This telnet shall go – you will find command prompt blank means port is open
If it says Connect Failed port is not open for IP address

User need to get these required ports open from the Internet service provider.

Tr@de X'press technical requirement

- 1) Tr@ade Lite & Tr@ade X'press is compatible on 1024 * 768 pixel size
- 2) Java setup is required to view the streamer & top Menu
(J2SE Runtime Environment 5.0 Update 5 & Above)

Trading Website Global IP address (www.anandrathi.com) = 202.87.57.100

Port required to open to view Tr@de X'press (streaming market watch) on
www.anandrathi.com

Sr. No.	Process	Global IP	Required Ports
1	Tr@de X'press	202.87.57.102	443
2	Alerts	202.87.57.102	5000 & 5002

telnet 202.87.57.102 443

telnet 202.87.57.102 5000
telnet 202.87.57.102 5002